



WM Programmable Tap Sensor With Blue Insert



AC02-024

WM Programmable Tap Sensor With Blue Insert

WM Programmable tap sensor with Blue Insert.
Adjustable settings include; run-on time, sensor range, purge and more.
Compatible with most DVS taps.

Technical data

Material	316 Stainless Steel
Gross weight	0.2 kg
Surface finish	Brushed
Operation type	A.I.R (Active Infrared) touch-free
Type of mounting	Wall mounted (\varnothing 27mm drill hole required)
Cable length	850mm

Adjustable settings

Run time	2, 5, 10, 15, 20 & 30 Seconds (Default 2 seconds)
Wave-on / Wave-off operation	ON/OFF (Default OFF)
Anti Vandal time	30 secs, 1, 2, 4 & 8 mins (Default 1 Minute)
Automatic purge	30 secs, 1, 2, 4 & 8 mins (Default 1 Minute)
Lock outs	OFF, 4, 6, 8 & 10 ops (Default OFF)